


WARNINGS

- **Battery MUST be in ON position when charging** (Fig. 1).
- Do not modify or disassemble the battery pack.
- Do not allow the battery pack to come in contact with fire or water.
- Do not charge the battery with any charger other than that supplied in this kit: **DO NOT** use the compressor AC adapter (sold separately) to charge battery.
- To prevent deterioration or damage of the battery **DO NOT** drop or subject to physical shock.
- Do not place the battery pack on flammable materials (such as in the bed or carpets) during charging.

Figure 1 Battery switch OFF = "O" and ON = "I."



Be sure to check out **The Aprehend Channel** on YouTube for instructional videos and tech tips.



Questions? View our online documentation and tutorials at www.rockwelllabs.com. For technical support call 800-891-8610 ext 0, or email sales@rockwelllabs.com.

Aprehend[®]

Biological Bed Bug Control

www.rockwelllabs.com

Rockwell Labs Ltd
creating the future of pest control™

www.rockwelllabs.com

03017

Aprehend[®]
Biological Bed Bug Control



Rechargeable Lithium Battery

For Aprehend Spray Kit

Part # APRS114 • Model YB1203000



IMPORTANT

Please read and follow battery charging and use instructions carefully.




Package Contents:

- A** (1) DC 12V 3000mAh Li-Ion Battery Pack Model YB1203000
- B** (1) Dual DC5521 Battery to Compressor Cable (compressor sold separately)
- C** (1) 5 Volt USB Wall Adapter
- D** (1) 5 to 12 Volt Transformer USB Charging Cable


**DO NOT use these instructions for the old battery pack model HBJ 12260.*

LED INDICATORS

There are 5 LED battery-strength indicators.




 **1 or 2 green lights:**
Do not run the compressor. Recharge battery prior to use, or product application will be compromised.

 **3, 4, or 5 green lights:**
Sufficient charge to run compressor.

CHARGING THE BATTERY



Battery *must* be in the ON position when charging.



Do *NOT* use the optional compressor AC adapter (Rockwell part #APRS135, sold separately) to charge the battery. Damage to the battery will occur.



NOTES & TIPS

- The battery comes partially charged. Apply a topping charge for 2–3 hours before use.
- To ensure long battery life do not discharge completely.
- Recharge the battery every 3 months when not in use. Never leave the battery in the discharged state for long periods.
- All lithium-ion rechargeable batteries are consumables and have a limited lifespan. Capacity and performance will decline over time. Contact us for replacement units.
- It's a good idea to have at least one spare battery and rotate their use to ensure consistent work flow.

- Recharge battery frequently.
- The compressor has an auto-off feature: when the gun is connected via the air hose, the compressor will run to reach optimum spray pressure, then rest until the trigger button on the gun is depressed. Battery consumption during auto-off rest is minimal. However, always turn the battery off between jobs to preserve battery life.
- The battery is designed for a slow charge process (8 ~ 10 hours for full charge). An extended, uninterrupted, complete charge extends battery life.

Charging the battery via wall outlet or direct USB

- Connect the battery to the USB charging cable. Plug the USB end into the wall adapter block or a direct USB charging port, such as in your vehicle.
- Place the switch on the battery to the ON position "I".
- A **RED** light indicates that the battery is charging. When the battery is fully charged, the **GREEN** light will illuminate.
- Disconnect the charger, and switch the battery to the off position "O" until use.



Using the legacy car charger (sold separately)

- Connect the battery to the charger and place the switch on the battery to the ON position "I".
- When plugging the car charger into the car socket (without the battery attached), the light will be **GREEN**.
- When the battery is attached, the charger light should change to **RED**.
- When fully charged, the light will illuminate **GREEN**.



Note: the car charger is no longer supplied with the sprayer kit. It is sold separately. To obtain a car charger, order Rockwell part #APRS116.